



Outdoor TV-SAT mixer

MIX2L series

art. 12-007
MIX2L TV 12V-SAT

This outdoor TV-SAT mixer is ideal to combine the signals of a TV multiband amplifier with signals coming from a SAT amplifier or directly from the LNB and distribute them to the outlets on a single cable.

Characteristics

- The commutation control and tone switching are enable on SAT input
- On TV input it is enable the remote power supply for a potential outdoor TV multiband amplifier
- Realized into shielded housing with F connectors
- Equipped with a plastic case and dedicated accessory for fixing to the mast.



Code	12-007	
Item	MIX2L TV 12V-SAT	
No. of TV inputs	1	
No. of SAT inputs	1	
No. of outputs	1	
TV frequencies	MHz	47÷862
SAT frequencies	MHz	950÷2150
Ch. R frequencies	MHz	5÷40
TV freq. insertion loss	dB ±1	1,7
SAT freq. insertion loss	dB ±1	1,8
Ch. R freq. insertion loss	dB ±1	0,8
Ch. R return loss	dB	> 15
Inputs isolation	dB	> 28
Dimensions (LxWxH)	mm	77x50x85
Packaging dimensions (LxWxH)	mm	100x90x54
Packaging weight	Kg	0,13
Fit temperature	°C	-10 ÷ +55
Compliant to	EN 55083-2, EN 60065	

Technical data refer to a temperature of 25 °C

Example of application

