



Indoor TV-SAT mixer

MIX2X series

art. 12-010
MIX2X TV-SAT

This indoor TV-SAT mixer is ideal to combine the signals of a TV multiband amplifier with signals coming from a SAT amplifier or directly from the LNB and distribute them to the outlets on a single cable.

Characteristics

- The commutation control and tone switching are enable on SAT input
- Realized into shielded housing with F connectors



Code	12-010	
Item	MIX2X TV-SAT	
No. of TV inputs	1	
No. of SAT inputs	1	
No. of outputs	1	
TV frequencies	MHz	47÷862
SAT frequencies	MHz	950÷2150
Ch. R frequencies	MHz	5÷40
TV freq. insertion loss	dB ±1	1,7
SAT freq. insertion loss	dB ±1	1,8
Ch. R freq. insertion loss	dB ±1	0,8
Ch. R return loss	dB	> 15
Inputs isolation	dB	> 28
Dimensions (LxWxH)	mm	55x22x42
Fit temperature	°C	-10 ÷ +55
Compliant to	EN 55083-2, EN 60065	

Technical data refer to a temperature of 25 °C

Packaging		
Package		multipla
Quantity	n.	5
Packaging dimensions (LxWxH)	mm	127x61x45
Packaging weight	Kg	0,27

Example of application

