



Indoor TV-SAT mixer

MIX DIGIT series

art. 22-010
MIX TV-SAT DIGIT

This indoor TV-SAT mixer is ideal to combine the signals of a TV multiband amplifier with signals coming from a SAT amplifier or directly from the LNB and distribute them to the outlets on a single cable.

Characteristics

- The commutation control and tone switching are enable on SAT input.
- Realized in die-casting housing
- Equipped with shielded fixing clamps



Code	22-010	
Item	MIX TV-SAT DIGIT	
No. of TV inputs	1	
No. of SAT inputs	1	
No. of outputs	1	
TV frequencies	MHz	47÷862
SAT frequencies	MHz	950÷2150
Ch. R frequencies	MHz	5÷40
TV freq. insertion loss	dB ±1	2
SAT freq. insertion loss	dB ±1	2
Ch. R freq. insertion loss	dB ±1	0,8
Ch. R return loss	dB	> 15
Inputs isolation	dB	> 28
Dimensions (LxWxH)	mm	56x20x18
Fit temperature	°C	-10 ÷ +55
Compliant to	EN 55083-2, EN 60065	

Technical data refer to a temperature of 25 °C

Packaging		
Package		multi-pack
Quantity	pcs	10
Packaging dimensions (LxWxH)	mm	130x61x42
Packaging weight	Kg	0,68

Example of application

