



## Outdoor TV mixer

### broadband and channel inputs LK series

# art. 22-162

## MIX2LK U-36/38 e 49/52 e 56



This outdoor TV mixer is ideal in those areas where  **MEDIASET** muxes (ch. 36, 38, 49, 52 and 56 and ch. 50 3D-Free) are received from a different direction compared to that of the **Rai** and other broadcasters muxes.

Realized to combine the signals of two antennas and distribute them to the TV on a single cable. Characterized by a filtered channels input and corresponding traps on the broadband input to block the interfering signals.

### Characteristics

- Shielded housing with screw F-type connectors
- Using slide switches, a remote power supply can be provided on input connectors
- Fixing accessory suitable for masts up to  $\varnothing$  60 mm included

Code	22-162	
Item	MIX2LK U-36/38e49/52e56	
No. of inputs	2	
Ch. UHF insertion loss	dB $\pm$ 1	$\leq$ 5
UHF band insertion loss	dB $\pm$ 1	< 4
Channel bandwidth	MHz $\pm$ 1	9
Channel selectivity	dB	> 16
Dimensions (LxWxH)	mm	142x60x130
Packaging dimensions (LxWxH)	mm	145x60x140
Packaging weight	Kg	0,6
Fit temperature	$^{\circ}$ C	-10 $\div$ +55
Compliant to	EN 55083-2, EN 60065	

Technical data refer to a temperature of 25  $^{\circ}$ C

### Example of application

