



Outdoor multiband amplifier 12V broadband and channel inputs ACK series

art. 28-068

ACK3/10 V-4+1Can.U-5 12V



Outdoor multiband amplifier with broadband and channel inputs, indicated for small size TV systems, ideal to receive:

- from one direction, the channels of band 4 plus one band 5 channel (e.g. ch. 40);
- from a second direction, all band 5 channels except the one received on the other input.

This amplifier is designed to optimize the amplification of DTT signals in the range E05÷E12+E21÷E48, attenuating the 700 MHz band without preventing the proper functioning of the channel E48.

The three inputs are so distributed:

- 1 VHF band input;
- 1 band 4 + 1 band 5 channel input;
- 1 band 5 input.

Each input is equipped with a coaxial attenuator (0÷20 dB) as level regulator and a switch to enable remote power supply, with the exception of 4+1Can.U input which is equipped with two coaxial attenuators (1 for the band 4 and 1 for the band 5 channel).

Created with calibration on request. When ordering you must specify:

- the last channel of the band 4 and the first of the band 5;
- the band 5 channel which you want to be included in 4+1Can.U input.

Characteristics

- Shielded housing with screw F-type connectors
- Separate amplification for the VHF and UHF bands
- All broadband inputs are amplified
- Fixing accessory suitable for masts up to Ø 60 mm included

Code	28-068	
Item	ACK3/10 V-4+1Can.U-5 12V	
No. of inputs	3	
No. of adjustments (0÷20 dB)	4	
VHF band noise figure	dB	4
UHF band noise figure	dB	5
VHF band max output level*	dBµV	110
UHF band max output level*	dBµV	120
VHF input gain	dB ±2	12
4+Can. input gain	dB ±2	10-10
5 input gain	dB ±2	9
Absorbed current	mA	90
Supply voltage	Vdc	12
Dimensions (LxWxH)	mm	142x60x130
Packaging dimensions (LxWxH)	mm	145x60x140
Packaging weight	Kg	0,5
Fit temperature	°C	-10 ÷ +55
Compliant to EU directives		2014/53/UE, 2011/65/UE

* Maximum output level measured with the method IM3 -35dBc 2 tones.
Technical data refer to a temperature of 25 °C

Example of application

