



Indoor tap FUSION series

art. 27-211 P1-8

Ideal for the distribution of the TV-SAT signals in the 5÷2150 MHz frequency range.

It has an input, a through-low loss output and one tap output.

It is an indoor product, realized in die-casting housing with screw F-type connectors.

Provided with a directional passage of current on the tap output.

Compatible with the signals for the return line.

Characteristics

- Realized in die-casting housing with screw F-type connectors
- One through-low loss output and one tap output
- Passage of current on both the outputs



Code	27-211	
Item	P1-8	
No. derived outputs	1	
Frequencies range	MHz	5÷2150
Tap loss TV	dB ±1	8,5
Tap loss SAT	dB ±1	8
Tap loss Ch. R	dB ±1	7
Throughpass loss TV	dB ±1	1,8
Throughpass loss SAT	dB ±1	3,2
Throughpass loss Ch. R	dB ±1	2,8
Inversed loss TV	dB ±1	>33
Inversed loss SAT	dB ±1	>18
Inversed loss Ch. R	dB ±1	>22
Return loss Ch. R	dB	>13
Connectors	screw F-type	
Dimensions (LxWxH)	mm	53x39x26
Fit temperature	°C	-10 ÷ +55
Compliant to	EN 55083-2, EN 50083-4, EN 60065, EN 60728-11	

Technical data refer to a temperature of 25 °C

Packaging		
Package	multi-pack	
Quantity	pcs	10
Packaging dimensions (LxWxH)	mm	185x100x50
Packaging weight	Kg	0,56

Operation scheme

