



Outdoor TV mixer

broadband inputs L series

art. 22-057
MIX2L IND.

This outdoor TV mixer is ideal to combine the signals of two antennas and distribute them to the TV on a single cable.

Equipped with two broadband inputs for the reception of DTT signals in the range E02÷E69.

On request it can be provided with the possibility to enable the remote power supply.



Characteristics

- Shielded housing with screw F-type connectors
- Fixing accessory suitable for masts up to Ø 60 mm included

Code	22-057
Item	MIX2L IND.
No. of inputs	2
No. of outputs	1
Insertion loss	$\text{dB } \pm 1$
	< 4
Inputs isolation	dB
	> 30
Dimensions (LxWxH)	mm
	77x50x85
Packaging dimensions (LxWxH)	mm
	100x90x54
Packaging weight	Kg
	0,13
Fit temperature	$^{\circ}\text{C}$
	-10 ÷ +55
Compliant to	EN 55083-2, EN 60065

Technical data refer to a temperature of 25 °C

Example of application

