



Outdoor TV mixer

broadband inputs L series

art. 22-058
MIX2L V+U-U

This outdoor TV mixer is ideal to combine the signals of two antennas and distribute them to the TV on a single cable.

This mixer is designed to optimize the reception of DTT signals in the range E05÷E12+E21÷E48, attenuating the 700 MHz band without preventing the proper functioning of the channel E48.

The two inputs are so distributed:

- 1 VHF+UHF band input;
- 1 UHF band input.

On request it can be provided with the possibility to enable the remote power supply.



Characteristics

- Shielded housing with screw F-type connectors
- Fixing accessory suitable for masts up to Ø 60 mm included

| Code | 22-058 |
|------------------------------|----------------------|
| Item | MIX2L V+U-U |
| No. of inputs | 2 |
| No. of outputs | 1 |
| Insertion loss | dB ±1 |
| | < 3 |
| Inputs isolation | dB |
| | > 20 |
| Dimensions (LxWxH) | mm |
| | 87x48x105 |
| Packaging dimensions (LxWxH) | mm |
| | 110x120x60 |
| Packaging weight | Kg |
| | 0,20 |
| Fit temperature | °C |
| | -10 ÷ +55 |
| Compliant to | EN 55083-2, EN 60065 |

Technical data refer to a temperature of 25 °C

Example of application

