



SAT switch

for 2 decoders C2 series

**art. 17-681
C2**

Switch that allows to connect two SAT decoders to the same outlet, without disconnect either decoder alternatively.

This switch is equipped with a scart cable (with dedicated control cable).
 Contrary to models without control cable, this product can be used also in presence of decoders that supply a remote power also in standby mode (e.g.: SKY decoders).



Characteristics

- Shielded housing
- SCART cable with dedicated control cable
- Screw F-type connectors

Code	17-681	
Item	C2	
Frequencies range	MHz	40 ÷ 2150
No. of inputs		2
Insertion loss	dB	< 2
Separation between inputs	dB	> 30
Absorbed current	mA	30
Dimensions (LxWxH)	mm	55x22x55
Packaging dimensions (LxWxH)	mm	153x190x74
Packaging weight	Kg	0,42
Fit temperature	°C	-10 ÷ +55
Compliant to	EN 55083-2, EN 60065	

Technical data refer to a temperature of 25 °C

Example of application

